

Sorensen XG 1500 Series

1500 W

1500 Watt, 1U Programmable DC Power Supplies

6–600 V

- Industry Leading Power Density
– Up to 1500 Watts in 1U
- Standard Digital Interfaces – USB&RS232/485
- LXI Ethernet and Isolated analog interfaces
- Power Factor Correction-PFC and universal AC input
- “Green” Sleep Mode – Automatically “sleeps” after period of non-use
- Built in sequencing - Unload your system controller
- Programmable fold-back protection delay



2.6–187.5 A

~

110

220

ETHERNET RS232

The XG 1500 is an industry leading programmable DC power supply designed for test, production, laboratory, OEM and quality assurance applications. The XG 1500 is a 1500 Watt, 1U programmable power supply with constant voltage and constant current modes, automatic cross-over and numerous features enabling cost effective, easy integration.

Key Features

Easy Integration

XG 1500 has many control and indication signals such as shutdown, constant voltage (CV) vs. constant current (CC) mode indication, OVP, OCP, OTP, and so on. In addition, the logical-high or -low is free selectable. Thus enabling the XG 1500 to replace existing power supplies with little or no system engineering required.

Free selectable analog control range

Most DC power supplies provide a 0 to 5 or 0 to 10 V analog control range to control the DC output from zero to full DC output range. With the XG 1500, the analog control range is free selectable starting at 0V to an upper range between 2V and 10V. In other words, the analog programming interface range is freely adjustable.

Auxiliary DC output channels with control

In many ATE systems one or more low power, fixed voltage supplies are needed to provide electrical power for any periphery within the ATE cabinet. For this purpose, the XG 1500 provides two standard auxiliary DC output channels. Both auxiliary power channels are controllable directly from the front-panel or through SCPI commands. With these channels, it is possible to drive output-disconnect or polarity-reversal relays, without needing a complicated computer controlled relay board.

DC-waveforms through internal sequencing

To allow for extremely fast programming, sequences can be programmed into and stored in memory using standard SCPI commands through USB, RS-232/485, LXI or GPIB.

Variable Fan Speed Control

The XG 1500's innovative approach to fan speed is determined by internal heat sink temperature. This allows the fans to adjust to a constant optimal speed when the output of the supply is being pulsed. This also reduces noise and increases fan life.

Power Saving Standby Mode

When the XG 1500 has been in an idle state, the supply can go into “sleep mode”, much like a computer monitor. This will allow the user to save energy and minimize lab noise. Since an XG 1500 left in sleep mode is still “on” the user will have quicker access to an enabled output.

Key Modes

Output Auto Start Mode (Auto Restart)

The Auto Start mode establishes the state of the output of the power supply after recovery from a complete power cycle (all front panel LEDs are not illuminated), or after recovery from a PC failure or reboot. If Auto Start mode is set to On, the power supply output will return to its previous value. Also, after the loss of any remote digital control, the XG unit will remain active in its last programmed setting and will not disrupt any test process.

Auxiliary Auto Start Mode

The Auxiliary Auto Start mode determines the state of the auxiliary output after a complete power cycle (all front panel LEDs are not illuminated). With Auxiliary Auto Start mode turned to On, the auxiliary output will be activated after the power supply is powered up again.

Foldback Mode

Foldback mode is used to disable the output when a transition is made between the operating modes. The power supply will turn off/disable the output and lock in foldback mode after a specified delay if the power supply transitions into CV mode or into CC mode, depending on the foldback mode settings. This feature is particularly useful for protecting current or voltage sensitive loads. Foldback can be set to trigger a switch when transitioning from CV to CC mode or from CC to CV mode.



洛克儀器股份有限公司
Lock Instrument Co. Ltd

(台北)新北市中和區中正路764號6樓

TEL: (02)3234-6000

(新竹)新竹市北區光華二街72巷79號

TEL: (03)532-4199

官方網站: www.lockinc.com.tw

網路商店: www.pcstore.com.tw/lock

AMETEK
Programmable Power
9250 Brown Deer Road
San Diego, CA 92121-2267
USA

AMETEK
PROGRAMMABLE POWER

XG 1500 Series : Product Specifications

1500 W

Output				
Models	Output Voltage ¹	Output Current ²	Output Power ³	
XG 6-220	6 V	220 A	1320 W	
XG 8-187.5	8 V	187.5 A	1500 W	
XG 12.5-120	12.5 V	120 A	1500 W	
XG 20-76	20 V	76 A	1520 W	
XG 30-50	30 V	50 A	1500 W	
XG 40-38	40 V	38 A	1520 W	
XG 60-25	60 V	25 A	1500 W	
XG 80-19	80 V	19 A	1520 W	
XG 100-15	100 V	15 A	1500 W	
XG 150-10	150 V	10 A	1500 W	
XG 300-5	300 V	5 A	1500 W	
XG 600-2.6	600 V	2.6 A	1560 W	
Models	Line Regulation Voltage (0.005% of rated output voltage +2 mV) ⁴	Line Regulation Current (0.01% of rated output current +2 mA) ⁵	Load Regulation Voltage (0.005% of rated output voltage + 2 mV) ⁶	Load Regulation Current (0.02% of rated output current +5 mA) ⁷
XG 6-220	2.3 mV	24 mA	2.3 mV	49 mA
XG 8-187.5	2.4 mV	20.7 mA	2.4 mV	42.5 mA
XG 12.5-120	2.62 mV	14 mA	2.62 mV	29 mA
XG 20-76	3.0 mV	9.6 mA	3.0 mV	20.2 mA
XG 30-50	3.5 mV	7 mA	3.5 mV	15 mA
XG 40-38	4 mV	5.8 mA	4 mV	12.6 mA
XG 60-25	5 mV	4.5 mA	5 mV	10 mA
XG 80-19	6 mV	3.9 mA	6 mV	8.8 mA
XG 100-15	7 mV	3.5 mA	7 mV	8 mA
XG 150-10	9.5 mV	3 mA	9.5 mV	7 mA
XG 300-5	17 mV	2.5 mA	17 mV	6 mA
XG 600-2.6	32 mV	2.26 mA	32 mV	5.5 mA
Models	Output Noise (rms, 300 kHz)		Output Ripple (p-p, 20 MHz)	
	Voltage	Current ⁸	Voltage	
XG 6-220	8 mV	400 mA	50 mV	
XG 8-187.5	8 mV	319 mA	50 mV	
XG 12.5-120	8 mV	206 mA	50 mV	
XG 20-76	8 mV	136 mA	50 mV	
XG 30-50	8 mV	120 mA	50 mV	
XG 40-38	8 mV	81 mA	50 mV	
XG 60-25	8 mV	63 mA	50 mV	
XG 80-19	8 mV	45 mA	80 mV	
XG 100-15	8 mV	35 mA	80 mV	
XG 150-10	10 mV	29 mA	100 mV	
XG 300-5	25 mV	18 mA	150 mV	
XG 600-2.6	50 mV	11 mA	250 mV	

1. Minimum output voltage is guaranteed to be $\leq 0.2\%$ of the rated voltage at zero output setting.

2. Minimum output current is guaranteed to be $\leq 0.4\%$ of the rated current at zero output setting when measured with rated load resistance.

3. Total output power is also based on AUX1 Output Voltage (5V) and AUX1 Output Current (0.5 A) and AUX2 Output Voltage (15 V) and AUX2 Output Current (0.5 A).

4. From 85-132 Vac or 170-265 Vac, constant load.

5. From 85-132 Vac or 170-265 Vac, constant load.

6. From no load to full load, constant input voltage.

7. For load voltage change, equal to the unit voltage rating, constant input voltage.

8. For 6 V models the ripple is measured at 2-6 V output voltage and full output current. For other models, the ripple is measured at 10-100% output voltage and full output current.

Note: All specifications are subject to change.

XG 1500 Series : Product Specifications

Model	Maximum Recommended Remote Sense Line Drop Compensation per Line ⁹	Up-prog. Response Time, 0~Vmax ¹⁰	Efficiency ¹¹ (100/200 VAC input)
XG 6-220	1 V	60 ms	75/77%
XG 8-187.5	1 V	60 ms	77/80%
XG 12.5-120	1 V	60 ms	80/83%
XG 20-76	1.5 V	60 ms	82/85%
XG 30-50	2 V	60 ms	83/86%
XG 40-38	2 V	60 ms	83/87%
XG 60-25	3 V	60 ms	83/87%
XG 80-19	5 V	100 ms	83/87%
XG 100-15	5 V	100 ms	83/87%
XG 150-10	5 V	100 ms	83/87%
XG 300-5	5 V	150 ms	83/87%
XG 600-2.6	5 V	250 ms	83/87%
Model	Down-prog. Response Time: Full Load*	Down-prog. Response Time: No Load*	Over-Voltage Trip Point
XG 6-220	50 ms	300 ms	0.5-7.5 V
XG 8-187.5	50 ms	400 ms	0.5-10 V
XG 12.5-120	50 ms	500 ms	1-15 V
XG 20-76	50 ms	600 ms	1-24 V
XG 30-50	50 ms	700 ms	2-39 V
XG 40-38	50 ms	800 ms	2-44 V
XG 60-25	50 ms	900 ms	3-66 V
XG 80-19	80 ms	1000 ms	3-95 V
XG 100-15	100 ms	1200 ms	3-125 V
XG 150-10	150 ms	1800 ms	3-180 V
XG 300-5	150 ms	2200 ms	5-330 V
XG 600-2.6	250 ms	3500 ms	5-660 V

9. When using remote sense, the total of the load voltage and the load line drops must not exceed the rated output of the power supply. For example, for an XG 6-220 in an application with 1 V of load line loss (0.5 V/Line), the maximum available load voltage would be 6-1=5 V. Note: The unit may operate at higher output voltages than this, but there is no guarantee that the power supply will meet performance specifications. Ultimately, the upper limit of the output voltage will be determined by internal circuitry of the power supply (non-adjustable)

10. With rated, resistive load.

11. At 100/200 Vac input voltage and maximum output power.

Applies to all footnotes: Programming and Readback: RS-232, RS-485, USB built in. GP1B, Ethernet optional. Specifications are guaranteed from 1% to 100% of the rated output voltage, current, and power.

* Typical

Note: All specifications are subject to change.

AC Line Input Specifications			
Rated AC Input Voltage/Frequency	100–240 Vac, 47–63 Hz		
Operational AC Input Voltage/Frequency	85–265 Vac continuous, 47–63 Hz, single phase		
Input Current (at 100/200 Vac)	23/12 A		
Inrush Current (100/200 Vac)	Less than: 50 A		
Power Factor Correction	0.99@100/200 Vac, rated output power		
Programming Mode	APG	ISOL	Digital
Voltage & Current Output Voltage Programming	0-100% 2~up to 10 V, programmable		
Voltage & Current Output Resistive Programming	0-100% 2~up to 10 kΩ, programmable		
Voltage Output Resistor Programming	0-100% 2~up to 10 kΩ, programmable		
Output Voltage and Current Monitor	0-100% 2~up to 10 V, programmable		
Voltage Programming Accuracy (mV) ¹	± 0.5% of rated output voltage, max (0-4V/4K range)		± 0.1% of rated output voltage
Current Programming Accuracy (mV) ¹	± 1% of rated output current, max (0-4V/4K range)		± 0.2% of rated output current
Voltage Readback Accuracy (mV)	± 1% of rated output voltage		± 0.1% of rated output voltage
Current Readback Accuracy (mV)	± 1% of rated output current		± 0.2% of rated output current
Isolation (Prog and Readback Lines)	With respect to chassis potential: 500 V	With respect to: chassis potential: 600 V negative or positive main output 1500 V negative or positive auxiliary output 300 V	
Voltage and Current Programming Resolution			0.012% of full scale
Voltage and Current Readback Resolution			
Parallel Operation	Up to 4 units in master / slave	Up to 4 units in master / slave	Up to 4 units in master / slave
Series Operation		Up to 2 units (with external diodes)	Up to 2 units (with external diodes)
Constant Voltage (CV) Constant Current (CC) Indicator	CV: TTL High (4-5 V) CC TTL Low (0-0.6 V)		
Shutdown Control ²		Logic low 0.0 - 1.4 V Logic high 2.0 - 15 V Dry contact compatible	
AUX On/Off Control		TTL level or dry contact compatible	
Power Supply Status Signal		TTL high: OK (4-5 V) TTL low: fail (0-0.6 V)	
Interlock Enable/Disable		Dry contact. Open/Short: On or Off programmable	

1. Typical APG or isolated APG accuracy can be improved to max accuracy by user calibration at the specific range selected

2. The shutdown input has user selectable negative logic operation via front panel or remote digital input/output

Note: All specifications are subject to change.

XG 1500 Series : Product Specifications

Output Performance Specifications	
Temperature Coefficient	100 PPM/° C from rated output voltage, after a 30-minute warm-up*
Drift (8 hours)	0.05% of rated output voltage & current over an 8 hour interval with constant line, load & temperature, after a 30-minute warm-up
Hold-up Time	Typical 20 ms at any rated input line.
Transient Response Time ¹	Less than 1 ms for 6 V to 60 V models. Less than 2 ms for 80 V to 600 V models*
Meter Accuracy	0.5% ± 1 count
Aux output ³	+5 V: +0.4 V, -0.5 V at 0.4 A +15 V: +1.2 V, -1.4 V at 0.4 A
Isolation ²	1500Vac or 2121Vdc between mains terminals and accessible conductive parts / chassis ground. Output to chassis 500Vac.
Environmental Specifications (Indoor use)	
Operating Temperature Range	32°F to 122°F, 100% load (0°C to 50°C)
Storage Temperature Range	-4°F to 158°F (-20° C to 70°C)
Operating Humidity Range	30–90% RH (no condensation)
Storage Humidity Range	10–95% RH (no condensation)
Operating Altitude	Up to 6,500 feet (2,000 m)
Installation Category	II (IEC 1010-1)
Pollution Degree	2 (IEC 1010-1)
Regulatory Approvals	
Safety	CSA 22.2 No. 61010-1, 60950-1-07 and UL61010-1, UL60950-1-(2nd Ed) ² . Marked with cCSAus, CE for EMC & low voltage directive
EMC	Complies with EN61326-1 Complies with EN55022, Class A, FCC Part 15A for conducted emissions Complies with EN55022, Class A, FCC Part 15A for radiated emissions Complies with EN61000-4 series of standards for immunity
Mechanical Specifications	
XG 1700 Watt (W×H×D)	16.8 x 1.7 x 19.0 inch (429 x 43.6 x 483 mm without rack mount ears)
Weight	22 lb (10 kg)
Cooling	Forced air cooling by internal fans

- * Typical
 1. Time for the output voltage to recover within 0.05% at its rated output for a load change 10-90% of rated output current. Output set point 10-100%
 2. Double insulation on primary to secondary isolation barriers. Basic insulation primary to protective earth ground.
 3. Current: 0.51 A minimum guaranteed, 0.72 A typically available. Overcurrent protection (each output) is automatic, non-latching. When OCP is tripped the aux voltage folds back and will recover to nominal condition when the over current condition is removed (typ. <0.2A). To protect external circuits attached to the aux outputs it is recommended that customers use an appropriately rated fuse in series with the aux outputs set point 10-100%

Note: All specifications are subject to change.

Model Number Description	
<p style="text-align: center;">XG 33 - 50 (XXX)</p> <p style="text-align: center;">Series Voltage Current Options</p>	
XG Options	
MEB	LXI Class C ETHERNET
MGA	GPIO, IEEE 488.2
MIA	Isolated Analog Interface
XG Options and Accessories	
RM - XG1	Rackmount Angle Brackets

